

# SWIVELIER

ADJUSTABLE LIGHTING

## SCREW-IN SUPER SPOT HALOGEN LOW VOLTAGE LIGHT CONVERTER



**22800**  
Shown with AR-111 lamp



**22800**  
Shown with PAR-36 lamp

## SCREW-IN SUPER SPOT HALOGEN SWIVEL LIGHT EXTENDERS



**22805**



**22806**

### One Light Super Spot Halogen Screw-In Light Converter

**22800:** Non-adjustable Screw-In Converter (BK or WH finish)  
Overall Length 5-1/2", Width 4-3/4"

### Adjustable Super Spot Halogen Screw-In Extenders

#### One Light Super Spot

**22805:** 5" Stem, 12-1/2" O.L.

**22808:** 8" Stem, 15-1/2" O.L.

**22811:** 11" Stem, 18-1/2" O.L.

#### Two Light Super Spot

**22806:** 5" Stem, 12-7/8" O.L.

**22809:** 8" Stem, 15-7/8" O.L.

**22812:** 11" Stem, 18-7/8" O.L.

Super Spot ring & swivel dimensions: Length 5-3/4"; Width 4-3/4"

**Lamps:** Use up to 75 Watt AR-111 or PAR-36 low voltage Halogen reflector 12 volt lamps (lamps not included)

**Specify Color:** (AL) Silver Aluminum, (BK) Black, (WH) White

**Accessory: Close-Up Cover Plate 29010** (8" dia.) or **29011** (6" dia.)

Use with 5", 8" or 11" stem Extender models to cover recessed fixture opening.

## AR-111 & PAR-36 LOW VOLTAGE SCREW-IN LIGHTS

Swivelier Light Converter and Extender units offer an easy and economical means to convert a medium base 120v fixture to use 12v AR-111 or PAR-36 lamps up to 75 watts. Available with different reflector designs, these lamps offer a variety of beam spreads from very narrow pin spots to extreme wide floods.

### LIGHT CONVERTER

Most existing ceiling, track, or recessed lights are easily converted to low voltage by simply removing the existing lamp and screwing in the Light Converter. Replace a PAR-38 lamp with either a 12v AR-111 or PAR-36 lamp. Compact in size, the light converter maintains similar dimensions of a PAR-38 lamp.

### SCREW-IN EXTENDERS

With a simple turn of your wrist, existing rigid fixtures or recessed down lights can become instantly adjustable and energy efficient. Easily place light illumination in any direction needed.

Male medium screw-in base features a built-in ratchet mechanism that prevents over tightening of lamp.

Built-in 75 watt miniature electronic transformer converts 120v medium base socket to 12v. Transformer is fully dimmable with a standard incandescent dimmer.

Swivelier's patented spring tension swivel rotates a full 360° and angles 90°. The swivel socket stays put without levers or set screws. A touch of the finger puts the light in any direction you desire for maximum flexibility.