

SWIVELIER

ADJUSTABLE LIGHTING

DELUXE 2-1/8" SOCKET EXTENSION NON-ADJUSTABLE EXTENDER MEDIUM BASE TO MEDIUM BASE 4KV PULSE RATED SOCKET FOR UP TO 250 WATT LAMPS



29981

**29981: 2-1/8" Socket Extender
Medium to Medium Base Rated 660W - 600V**

Overall Length: 3-1/4"

Outside Diameter: 1 1/2"

Extends Socket: 2-1/8"

Lamps: Up to 250 Watt PAR-38 Reflector Lamps
(lamps not included)

SOCKET EXTENDER RETROFIT LIGHT CONVERTER

Socket Extension easily screws into an existing medium base socket and allows you to extend lamp an additional 2-1/8 inches.

The male screw in base features a built-in ratchet mechanism that prevents over tightening of lamp.

Use independently, or in conjunction with suitable existing recessed fixtures.

Convert deep recessed housings, or other lighting fixtures to accommodate PAR-38 lamps that replace R-40 lamps.

Ideal retrofit for short neck PAR-30 lamps that replace longer R-30 or long neck PAR-30 lamps.

To use with a metal halide lamp, the fixture must have appropriate ballast. (ballast not included).

Use also to retrofit with medium base Compact Fluorescent self-ballasted lamps.

- **High quality porcelain 4KV pulse rated socket**
- **Copper, nickel plated, female screwshell**
- **Brass, male screwshell**
- **Rated 660 W - 600 V**
- **For use with up to 250 watt medium base Halogen or Metal Halide reflector lamps on 120v to 277v**